



**Note: This API call is for DOS and Win16 personality only. Use [Family API](#) for portability.**

2018/09/07 05:04 · prokushev · [0 Comments](#)

# Int 21H, AH=06H

## Version

1 and higher

## Brief

DIRECT CONSOLE OUTPUT/INPUT

## Family API

[DosWrite](#) [DosRead](#)

## Input

```
AH = 06h
DL = output character (except FFh)
DL = FFh - input character
```

## Return

On output:

```
AL = character output (despite official docs which state nothing is
returned) (at least DOS 2.1-7.0)
```

On input:

```
ZF set if no character available
    AL = 00h
ZF clear if character available
    AL = character read
```

## Notes

does not check ^C/^Break

writes to standard output, which is always the screen under DOS 1.x, but may be redirected under DOS 2+

if the returned character is 00h, the user pressed a key with an extended keycode, which will be returned by the next call of this function

this function reads from standard input, which is always the keyboard under DOS 1.x, but may be redirected under DOS 2+

although the return of AL=00h when no characters are available is not documented, some programs rely on this behavior

## See also

AH=02h,AH=09h,AH=0BH

## Note

Text based on [Ralf Brown Interrupt List Release 61](#)

<b>DOS API</b>	
Process manager	<a href="#">INT 20H</a> , <a href="#">INT 21H</a> : <a href="#">00H</a> , <a href="#">25H</a> , <a href="#">26H</a> , <a href="#">31H</a> , <a href="#">34H</a> , <a href="#">35H</a> , <a href="#">4BH</a> , <a href="#">4CH</a> , <a href="#">4DH</a> , <a href="#">50H</a> , <a href="#">51H</a> , <a href="#">52H</a> , <a href="#">55H</a> , <a href="#">62H</a> , <a href="#">INT 22H</a> , <a href="#">INT 27H</a> , <a href="#">INT 28H</a>
File manager	<a href="#">INT 25H</a> , <a href="#">INT 26H</a> , <a href="#">INT 21H</a> : <a href="#">0DH</a> , <a href="#">0EH</a> , <a href="#">0FH</a> , <a href="#">10H</a> , <a href="#">11H</a> , <a href="#">12H</a> , <a href="#">13H</a> , <a href="#">14H</a> , <a href="#">15H</a> , <a href="#">16H</a> , <a href="#">17H</a> , <a href="#">19H</a> , <a href="#">1AH</a> , <a href="#">1BH</a> , <a href="#">1CH</a> , <a href="#">21H</a> , <a href="#">22H</a> , <a href="#">23H</a> , <a href="#">24H</a> , <a href="#">27H</a> , <a href="#">28H</a> , <a href="#">29H</a> , <a href="#">2EH</a> , <a href="#">2FH</a> , <a href="#">32H</a> , <a href="#">3305H</a> , <a href="#">36H</a> , <a href="#">39H</a> , <a href="#">3AH</a> , <a href="#">3BH</a> , <a href="#">3CH</a> , <a href="#">3DH</a> , <a href="#">3EH</a> , <a href="#">3FH</a> , <a href="#">40H</a> , <a href="#">41H</a> , <a href="#">42H</a> , <a href="#">4300H</a> , <a href="#">4301H</a> , <a href="#">45H</a> , <a href="#">45H</a> , <a href="#">46H</a> , <a href="#">4EH</a> , <a href="#">4FH</a> , <a href="#">54H</a> , <a href="#">56H</a> , <a href="#">5700H</a> , <a href="#">5701H</a> , <a href="#">5AH</a> , <a href="#">5BH</a> , <a href="#">5c00H</a> , <a href="#">5c01H</a> , <a href="#">60H</a> , <a href="#">67H</a> , <a href="#">68H</a> , <a href="#">6900H</a> , <a href="#">6901H</a> , <a href="#">6AH</a> , <a href="#">6CH</a>
Character Device I/O	<a href="#">INT 29H</a> , <a href="#">INT 21H</a> : <a href="#">01H</a> , <a href="#">02H</a> , <a href="#">03H</a> , <a href="#">04H</a> , <a href="#">05H</a> , <a href="#">06H</a> , <a href="#">07H</a> , <a href="#">08H</a> , <a href="#">09H</a> , <a href="#">0AH</a> , <a href="#">0BH</a> , <a href="#">0AH</a> , <a href="#">0CH</a> , <a href="#">5D07H</a> , <a href="#">5D08H</a> , <a href="#">5D09H</a> , <a href="#">5D0AH</a>
Signals	<a href="#">INT 23H</a> , <a href="#">INT 24H</a> , <a href="#">INT 21H</a> : <a href="#">3300H</a> , <a href="#">3301H</a> , <a href="#">3302H</a>
Memory manager	<a href="#">INT 21H</a> : <a href="#">48H</a> , <a href="#">49H</a> , <a href="#">4AH</a> , <a href="#">5800H</a> , <a href="#">5801H</a> , <a href="#">5802H</a> , <a href="#">5803H</a>
Date and Time	<a href="#">INT 21H</a> : <a href="#">2AH</a> , <a href="#">2BH</a> , <a href="#">2CH</a> , <a href="#">2DH</a>
Misc	<a href="#">INT 21H</a> : <a href="#">30H</a> , <a href="#">3306H</a> , <a href="#">3700H</a> , <a href="#">3701H</a> , <a href="#">3702H</a> , <a href="#">3703H</a> , <a href="#">59H</a>
NLS	<a href="#">INT 21H</a> : <a href="#">3303H</a> , <a href="#">3304H</a> , <a href="#">3800H</a> , <a href="#">3801H</a> , <a href="#">6300H</a> , <a href="#">6301H</a> , <a href="#">6301H</a> , <a href="#">6500H</a> , <a href="#">6501H</a> , <a href="#">6502H</a> , <a href="#">6503H</a> , <a href="#">6504H</a> , <a href="#">6505H</a> , <a href="#">6506H</a> , <a href="#">6507H</a> , <a href="#">6520H</a> , <a href="#">6521H</a> , <a href="#">6522H</a> , <a href="#">6523H</a> , <a href="#">65A0H</a> , <a href="#">65A1H</a> , <a href="#">65A2H</a> , <a href="#">6601H</a> , <a href="#">6602H</a>
Devices	<a href="#">INT 21H</a> : <a href="#">4400H</a> , <a href="#">4401H</a> , <a href="#">4402H</a> , <a href="#">4403H</a> , <a href="#">4404H</a> , <a href="#">4405H</a> , <a href="#">4406H</a> , <a href="#">4407H</a> , <a href="#">4408H</a> , <a href="#">4409H</a> , <a href="#">440AH</a> , <a href="#">440BH</a> , <a href="#">440CH</a> , <a href="#">440DH</a> , <a href="#">440EH</a> , <a href="#">440FH</a> , <a href="#">4410H</a> , <a href="#">4411H</a> , <a href="#">53H</a>
Network	<a href="#">INT 21H</a> : <a href="#">5E00H</a> , <a href="#">5E01H</a> , <a href="#">5E02H</a> , <a href="#">5E03H</a> , <a href="#">5E04H</a> , <a href="#">5E05H</a> , <a href="#">5F00H</a> , <a href="#">5F01H</a> , <a href="#">5F02H</a> , <a href="#">5F03H</a> , <a href="#">5F04H</a> , <a href="#">5F05H</a> , <a href="#">5F07H</a> , <a href="#">5F08H</a>

**osFree Macro Library**

Video I/O	@SetMode @SetCurSz @SetCurPos @GetCur @SetPage @ScrollUp @ScrollDn @Scroll @GetChAtr @PutChAtr @PutCh @SetPalet @SetColor @SetDot @GetDot @WrtTTY @VideoState @GetMode @GetDisplay @GetVideoState @GetEGAInfo @Cls
Hardware info	@Equipment @MemSize
Serial I/O	@AuxInit @AuxSendChar @AuxRecieveChar @AuxStatus
Tape I/O	@TapeOn @TapeOff @TapeRead @TapeWrite
Keyboard I/O	@KbdStatus @CharIn @CharPeek
Printer I/O	@PrnPrint @PrnInit @PrnStatus
Disk I/O	@DskReset @DskStatus @DskRead @DskWrite @DskVerify @DskFormat
Date and Time	@SetTime @GetTime
Mouse	@MouInit @MouShowPointer @MouStatus @MouSetPos @MouSetMickey @MouRegion
Memory manager	@ModBlok SET_BLOCK

2022/10/04 14:28 · prokushev · 0 Comments

2018/09/04 17:23 · prokushev · 0 Comments

**Family API**

DOS	Process Manager	DosBeep DosExit DosSleep DosExecPgm
	File Manager	DosChDir DosChgFilePtr DosClose DosDelete DosDupHandle DosMkDir DosMove DosQCurDir DosQCurDisk DosSetFileMode DosOpen DosQFileInfo DosRead DosQFileMode DosQFSInfo DosQVerify DosRmdir DosSelectDisk DosFindClose DosFindFirst DosFindNext DosSetFileInfo DosSetVerify DosWrite DosFileLocks DosSetFHandState DosNewSize DosBufReset DosQFHandState DosSetFSinfo DosShutdown
	Memory Manager	DosFreeSeg DosSubAlloc DosSubFree DosSubSet DosAllocHuge DosAllocSeg DosReallocHuge DosReallocSeg DosGetHugeShift DosCreateCSAlias
	NLS	DosCaseMap DosGetCtryInfo DosGetDBCSEv DosSetCtryCode DosGetCollate DosGetMessage DosInsMessage DosPutMessage
	Date and Time	DosSetDateTime DosGetDateTime
	Devices	DosDevConfig DosDevIOct1 DosDevIOct2
	Signals	DosHoldSignal DosSetSigHandler
	Misc	BadDynLink DosGetEnv DosGetMachineMode DosGetVersion DosError DosErrClass DosSetVec
KBD		KbdCharIn KbdFlushBuffer KbdGetStatus KbdSetStatus KbdStringIn KbdPeek
VIO		VioGetBuf VioGetConfig VioGetCurPos VioGetCurType VioGetPhysBuf VioReadCellStr VioReadCharStr VioScrollUp VioScrollDn VioScrollLf VioScrollRt VioScrUnLock VioSetCurPos VioSetCurType VioSetMode VioGetMode VioShowBuf VioWrtCellStr VioWrtCharStr VioWrtCharStrAtt VioWrtNAttr VioWrtNCell VioWrtNChar VioWrtTTY VioScrLock VioPopUp
Tools		BIND
Modules		DOSCALLS.DLL VIOCALLS.DLL KBDCALLS.DLL MSG.DLL
Libraries		API.LIB OS2386.LIB FAPI.LIB DOSCALLS.LIB SUBCALLS.LIB

2018/08/25 15:05 · prokushev · 0 Comments

From:

<https://www.osfree.ru/doku/> - **osFree wiki**

Permanent link:

<https://www.osfree.ru/doku/doku.php?id=en:docs:dos:api:int21:06&rev=1607322276>

Last update: **2020/12/07 06:24**

